尺寸: 90X100mm, 105G铜版纸, 双面折页,彩色印刷

B.O.W®

使用说明书

HB199

非常感谢您使用本公司为您提供的键盘，在使用本产品前请详细阅读本手册。

■ 产品展示

一款轻巧折叠式带支架的蓝牙键盘

■ 产品特点

1. 蓝牙三通道设备可同时使用于平板电脑、一体机电脑/台式电脑（需配蓝牙适配器）、手机等。
2. 按键人体工程学设计，改善指头与按键接触的感觉。
3. 全尺寸完美的按键布局，充分解决市面上所有因折叠结构而无法解决的按键布局缺陷等问题。
4. 小巧的体积设计方便携带完美解决传统键盘体积庞大、笨重的问题。
5. 快速充电，超长待机。
6. 键盘自带支架，可用于支撑平板、手机等设备。

■ 指示灯说明

键盘指示灯	指示灯颜色	指示灯状态
开机状态；电源指示灯	绿色	长亮<10秒后熄灭
蓝牙通道指示	蓝色	配对状态1秒5闪， 回连状态1秒1闪
充电指示灯	红色	充电常亮红色,充满熄灭
电量指示灯	蓝色	按FN+电量显示，三个通道指示灯同时闪连，每闪一下为25%电量

■ 支架使用方法

支架向左右两边摆动即可调节角度大小　　支架可放置手机或平板

■ 键盘连接步骤

1. 开机：打开开关，电源指示灯绿色亮起10秒，蓝牙1通道指示灯蓝色闪连，进入配对状态。

2. 配对

2.1

配对第一台设备：

1）第一次开机默认使用蓝牙通道1，开机后蓝牙1通道指示灯快闪蓝灯

2）手机/平板上出现键盘配对名“B.O.W”

3）点击此配对名，连接成功，1通道指示灯常亮蓝色

配对第二台设备： 1）FN+蓝牙2通道按键，蓝牙2通道指示灯快闪蓝灯

2）手机/平板上出现键盘配对名“B.O.W”

3）点击此配对名，连接成功，2通道指示灯常亮蓝色

配对第三台设备： 1）FN+蓝牙3通道按键，蓝牙3通道指示灯快闪蓝灯

2）手机/平板上出现键盘配对名“B.O.W”

3）点击此配对名，连接成功，3通道指示灯常亮蓝色

2.2 切换通道：按FN+通道1、通道2、通道3可在最切换对应的通道，相应的蓝牙指示灯闪烁蓝灯1秒1闪，回连成功后常亮蓝色。

2.3 重新配对设备：按FN+通道1、通道2、通道3选择蓝牙通道，然后按FN+pairing进入配对状态。

注意

1. 不能同时使用已连接好的三个设备，要按FN+相对应的通道即可切换。
1. 无须配对密码
2. 蓝牙键盘按下fn+左边的Shift+backspace恢复复出厂状态，三个通道指示灯蓝色亮一下,键盘默认为通道一。
3. 每个通道默认记忆最后一次使用的设备。
4. 在出厂状态下，单按 FN+ B/O/W直接进入配对状态;已连接过设备想重新更改连接设备的，按FN+pair启动配对状态。

■ 键盘快捷功能键说明

	Android系统	iOS系统	Windows系统
Fn+	Fn锁	Fn锁	Fn锁
Fn+ F1	屏幕亮度减	屏幕亮度减	屏幕亮度减
Fn+ F2	屏幕亮度加	屏幕亮度加	屏幕亮度加
Fn+ F3	主页	主页	打开网页
Fn+ F4	菜单	无功能	鼠标右键
Fn+ F5	返回	无功能	退出
Fn+ F6	上一曲	上一曲	上一曲
Fn+ F7	暂停/播放	暂停/播放	暂停/播放
Fn+ F8	下一曲	下一曲	下一曲
Fn+ F9	静音	静音	静音
Fn+ F10	音量减	音量减	音量减
Fn+ F11	音量加	音量加	音量加
Fn+ backspace Delete	后删	后删	后删
Fn+ F12 B	蓝牙通道1	蓝牙通道1	蓝牙通道1
Fn+ F12 O	蓝牙通道2	蓝牙通道2	蓝牙通道2
Fn+ F12 W	蓝牙通道3	蓝牙通道3	蓝牙通道3
Fn+ C Esc	启动配对	启动配对	启动配对
Fn+ Ctrl	搜索	搜索	搜索
Fn+ Alt	电量显示	电量显示	电量显示

Fn锁功能定义:单按可以减少F1-F12三键组合操作，只需按Shift+F1-F12，便会实现对应的功能

■ 键盘参数

蓝牙版本	Bluetooth 3.0
有效操作范围	8米内
调制方式	GFSK
工作电压	3.0-4.2V
工作电流	≤ 3.0mA
待机电流	<0.3mA
睡眠电流	<0.1mA
待机时长	≥150天
可持续工作时长	≥50个小时
充电时长	≤2个小时
锂电池容量	160mA
按键力	50~80g
按键寿命	300万次点击
支持系统	iOS / Android / Windows
键盘尺寸	202.5x89.2x5.5mm (展开时)

■ 节能休眠模式

当键盘30分钟内无任何操作指令时,键盘会自动进入休眠模式,需要使用时,只需要按任意键并等待≤10秒左右,键盘将会被唤醒,键盘可以进行正常工作。

■ 排除故障

如果您无法连接键盘到您的平板电脑，请尝试以下：
1. 确保设备和键盘电池有电量。
2. 检查设备和键盘的蓝牙是否已经打开。
3. 确保设备和键盘之间的距离当长内。

■ 特别提示

1. 对于其他可激活的蓝牙设备，在连接前请仔细核对蓝牙标准和兼容性。
2. 当键盘长期不使用时,我们建议关闭键盘电源,以延长电池寿命。

⚠ 警告：不遵循以下安全说明可能会导致起火、触电、损坏键盘设备

危险（高度危险警惕）　✗ 警告（中度危险要警惕）

⚠ 注意（轻微危险要关注）

✗ 远离利器

远离类似微波辐射源

✗ 禁止重物挤压

✗ 禁止冲击、弯曲键盘

⚠ 远离油类、化学、液体或者其他有机溶剂

B.O.W®

无线科技 无限生活

轻巧折叠带支架三通道蓝牙键盘

深圳市航世科技有限公司

地址：深圳市宝安区沙井民主西部工业区G区 航世科技园
网址：www.bow.co
有关产品技术交流群：211705564
全国服务热线：400-682-8008

B.O.W®

User Manual

HB199

Thank you for using the keyboard provided by BOW, please read this manual carefully before using this product.

■ Product display



■ Keyboard Characteristics

1. Bluetooth 3 channel suitable for Android & Windows & IOS systems tablets, smartphones, etc.
2. Keyboard with ergonomic design, improve the sense of touch between finger and keyboard. R angle key caps improve the visual effect.
3. Full size layout,convenient to type.
4. Foldable design,convenient to carry.
5. easy to charge,long time standby.
6. With two hideable and 90 degree rotatable stands,can hold tablet and cellphone devices.

■ Indicator light instruction

Keyboard status	Indicating light color	Indicating light status
Boot state:power indicator	Green	Stay 10s then be off
Bluetooth indicator	Blue	Pairing:Blue lights blinking quickly (5 times/s) Reconnecting:Blue lights blinking 1 time/s
Charging indicator	Red	Red light will turn on when charging the keyboard and turn off once fully charged
Power indicator	Blue	Press Fn+ keys, three channel indicator flash together, Three Bluetooth indicator lights all flash 1 time: 25% Battery

■ Stand instruction



• The stand swings to the right and left to adjust the angle　　• The stand can hold cellphone and tablet

■ Bluetooth keyboard pairing

Step 1: Power the keyboard on by unfolding it,power indicator bright on green stay 10s, ① light flash blue quickly;

Step 2 Paring

1) Pairing first device:1)he default first channel ① ,turn on the power switch, ① light flash blue quickly;
2) tablet and smartphone will find bluetooth device called B.O.W;
3) Click B.O.W. to connect, ① indicator stay blue after connected successfully.

Pairing second device:

1) Fn+ ②key, ② indicator flash quickly blue;
2) tablet and smartphone will find bluetooth device called B.O.W;
3) Click B.O.W. to connect, ② indicator stay blue after connected successfully.

Pairing third device:

1) Fn+ ③key, ③ indicator flash quickly blue;
2) tablet and smartphone will find bluetooth device called B.O.W;
3) Click B.O.W. to connect, ③ indicator stay blue after connected successfully.

1.**To switch the Bluetooth channel:** press Fn+ ①/②/③ switch to the corresponding Bluetooth,and the Bluetooth indicator flash blue 1 time/s,stay blue after connected successfully

2. **Repair device:** choose the Bluetooth channel by pressing Fn + ① /②/③ , then press Fn+pairing key to pair

Note:

1. The three connected device can not use at same time,pressing Fn+ ①/②/③ can switch.
2. No pairing code.
3. Press FN+ left shift +backspace restore factory settings,the three channel indicator flash blue,bluetooth 1-channel is default.
4. Every channel will remember the last connected channel.
5. In Factory state,just pressing FN+BOW can pair directly,changing the connected device,pressing FN+pair to repair.

■ Function Keys

Fn lock function:By pressing this key to reduce F1-F12 three keys operation,only need to press shift +F1-f12 to implement function.

FN+	Android	iOS	Windows
Fn Lock	Fn Lock	Fn Lock	Fn Lock
Brightness -	Brightness -	Brightness -	Brightness -
Brightness +	Brightness +	Brightness +	Brightness +
Home	Home	Home	Web Browser
Menu	Menu	N/A	Mouse Right Key
Back	Back	N/A	Exit
Previous Track	Previous Track	Previous Track	Previous Track
Play/Pause	Play/Pause	Play/Pause	Play/Pause
Next Track	Next Track	Next Track	Next Track
Mute	Mute	Mute	Mute
Volume -	Volume -	Volume -	Volume -
Volume +	Volume +	Volume +	Volume +
Delete	Delete	Delete	Delete
Bluetooth channel 1	Bluetooth channel 1	Bluetooth channel 1	Bluetooth channel 1
Bluetooth channel 2	Bluetooth channel 2	Bluetooth channel 2	Bluetooth channel 2
Bluetooth channel 3	Bluetooth channel 3	Bluetooth channel 3	Bluetooth channel 3
Enter Paring Mode	Enter Paring Mode	Enter Paring Mode	Enter Paring Mode
Battery Display	Battery Display	Battery Display	Battery Display
Search	Search	Search	Search
Head of Line	Head of Line	Head of Line	Head of Line
End of Line	End of Line	End of Line	End of Line
Previous Page	Previous Page	Previous Page	Previous Page
Next Page	Next Page	Next Page	Next Page

■ Keyboard Specification

1. Bluetooth version: Bluetooth 3.0
2. Operating distance is up to 10 meters
3. Modulation system: GFSK
4. Operation voltage: 3.1-4.2V
5. Operation current: <3mA
6. Standby current: <0.3mA
7. Sleeping current: <0.1mA
8. Standby time: ≥150 days
9. Uninterrupted working time: ≥50 hours
10. Charging time: ≤2 hours
11. Lithium battery capacity: 160mAh
12. Key force: 50-80g
13. Key Life: 3 million strokes
14. Support: iOS, Android, Windows
15. Size: 202.5*89.2*5.5mm(unfolding)

■ Energy Saving Sleep Mode

The keyboard will enter sleep mode when being idle for 30 minutes. To activate it , press any key and wait for 5 seconds.

■ Trouble Shooting

If you can not connect the keyboard with you tablet, please try as follow:
1.Make sure your tablet and Bluetooth keyboard are powered.
2.Check if bluetooth of the device and keyboard is open.
3.Make sure the distance between device and keyboard is within 8m.

■ Special Notice:

1. For other activated Bluetooth devices, check the Bluetooth standards and compatibility carefully before you connect.
2. When do not use keyboard for long time, we suggest you switch off the keyboard power to prolong the life of the battery.

■ Safety Caution

⚠ Warning: it can cause fire, electric shock, damage of keyboard system if disobey the safety notes.

Dangerous (be careful of highly dangerous)

✗ Warning (be careful of mid dangerous)

⚠ Caution (slight dangerous should be noted)

✗ 1)Keep the keyboard away from sharp objects.
2)Do not Microwave the keyboard.
✗ 3) Do not place heavy object on the keyboard.
✗ 4) Do not force or distorted the keyboard.
⚠ 5) Keep away from oil, chemical or any other organic liquid.

B.O.W®

Wireless technology, infinite life

Foldable Mini Keyboard with Hideable Stand

Shenzhen Hangshi Technology Co.,Ltd.
ADD: Hangshi Technology Park, G Area, Democracy West Industry park Shajing Baoan District Shenzhen China
Web: www.bow.co
QQ group about exchange of skills: 211705564
Nationwide service volume line: 400-682-8008